



ΘΥΡΟΤΗΛΕΦΩΝΟ  
HT 501 / HT 802



	STR 2003/2	ACET 701	ACET 901	AIPPHONE VC-K	AMPLIVOX 2211	BITRON AN 0002	BPT	BPT AZ 72 TB	CITIFONIX	CITOVOX	COMELIT OKAY	COMELIT VOX 2000
O	O	6	3	3	0	6	4	3 5	2	9	4	4
S	S	5	4	B	1	11	3	7	5	T	1	1
M	M	4	2	2	R	1	1	4	1	10	3/6	3
T	T	3	1	1	T	2	5	6	4	7	2	2
1	1	7	5	4	Z	9	2	8	3	5	5	P1



ΘΥΡΟΤΗΛΕΦΩΝΟ  
HT 501 / HT 802



	ELVOX 870	FARFISA PT 510	FERMAX GONDOLA	FERMAX REKTO TF-4	GOLMAR T-600	GOLMAR T-800	GOLMAR T-100A	GOLMAR M-500 T-2800, T-2802	COMELIT OKAY	LT 600
O	4/5 3	3	3	C	3	3	3	3	4	3
S	6	6	V/5	E	6	0	12	7	1	6
M	2	1	1	A	1	5	5	5	3/6	1
T	1	2	2	B	2	10	10	10	2	2
1	7	5	4	P	1	P1	11	4	5	T

ΘΥΡΟΤΗΛΕΦΩΝΟ HT 501 / HT 802	LT-LEG.603R	LT-LEG.630 WS	LT TERRANEO 603N	PAGANI COMPACT- 71	RITTO ELEGANT 40518	SELT I	SELT I SL/254	SIEDLE HT 611- 01	SIEMENS	SIEMENS	TESLA DDZ 85	TESLA DDZ 85
1	5	T	T1	A	11	TV	5	1	11	8 7	1	Z
T	1	2	2	2	15	1	2	11	2	4	6	6
M	6	1	1	1	12	2	1	2	7	9	2	2
S	3	6	8	3	14	7	6	7	3	10	4	4
O	T	3	3	0	13	8	3 7	9 C	14 1	7 8	3	3

Για το SIEMENS  
να χρησιμοποιηθεί  
βομβητής 6V συνεχές

ΘΥΡΟΤΗΛΕΦΩΝΟ HT 501 / HT 802	URMET 1130	VIDEX
1	8 9	5
T	1	1
M	2	6
S	7	3
O	11	T

ΘΥΡΟΤΗΛΕΦΩΝΟ HT 502 / HT 902	SILVESTRON	COMELIT MEΛ. HXO	BITRON 0077 ΜΕΛΩΔΙΚΟΣ	TEGUI
D	E	S	C	1E
1	O	R1	9	3
O	1	4	6	2
M	2	3	2	4
T	3	2	1	5